



AUGUSTOPEREIRA

The future is now!

DVB[®] S S₂ T T₂ C C₂

A/TV

MEDIDOR DE CAMPO

Ref: 02201TSC1000



AMIKO TSC 1000, Digital Meter

MAIN FEATURES

- DVBS/DVBS2/DVBT/DVBT2/DVBC/DVBC2/ATV.
- LNB short-circuit protection and indicator.
- Satellite Locator.
- Real time angle calculation.
- Extremely fast and accurate with high sensitivity.
- 320*240 color LCD display with controllable back light.
- Database editable by user easily.
- Signal lock audible notification.
- All DiSEqC protocol monitor based on 22KHz signal.
- Database can be edited on PC and downloaded by USB port.
- Ultra-long standby, low power consumption.
- Fast charging Li-ion battery can last around 3 hours.

TECHNICAL SPECIFICATIONS

DVB-T

Bit Error Rate (BER)	CBER (before Viterbi): $1E-7 - 1E-3$ VBER (before Reed Solomon): $1E-7 - 1E-3$
Frequency range	42-1005MHz
Power level	30-100 dBμV, +/-2dB
Modulation Error Rate(MER)	5 - 35dB, +/-0.5dB
Bandwidth	6MHz, 7 MHz, 8 MHz
FFT type	2k, 8k
Constellation	QPSK, 16QAM, 64QAM
Viterbi rate	1/2, 2/3, 3/4, 5/6, 7/8
Guard interval	auto
Spectrum inversion	auto

DVB-T2 / T2 Lite

Bit Error Rate (BER)	CBER (before LDPC): $1E-7 - 1E-3$ LBER (before BCH): $1E-9 - 1E-5$
Frequency range	42-1005MHz
Power level	30-100 dBμV, +/-2dB
Modulation Error Rate(MER)	5 - 35dB, +/-0.5dB
Bandwidth	1.7MHz, 5MHz, 6MHz, 7 MHz, 8 MHz
Mode	SISO, MISO, PLP single or multiple
FFT type	1k, 2k, 4k, 8k, 16k, 32k + extended bandwidth
Constellation	QPSK, 16QAM, 64QAM, 256QAM
Viterbi rate	1/2, 3/5, 2/3, 3/4, 4/5, 5/6, 1/3, 2/5
Guard Interval	auto
Spectrum inversion	auto

DVB-C

Bit Error Rate (BER)	BER (before Reed Solomon): $1E-7 - 1E-3$ PER (Packet Error Rate): $1E-6 - 1E-2$
Frequency range	42-1005MHz
Power level	35-100 dBμV, +/-2dB
Modulation Error Rate(MER)	20 - 40dB, +/-0.5dB
Symbol Rate	1.7 to 7.2 Msym/s
Constellation	16QAM, 32QAM, 64QAM, 128QAM, 256QAM
Spectrum inversion	auto

DVB-C2

Bit Error Rate (BER)	CBER (before Reed Solomon): $1E-7 - 1E-3$ LBER (Packet Error Rate): $1E-9 - 1E-5$
Frequency range	42-1005MHz
Power level	30-100 dBμV, +/-2dB
Modulation Error Rate(MER)	5 - 35dB, +/-0.5dB

Bandwidth	6MHz, 8 MHz
FFT type	4k
Constellation	16QAM, 64QAM, 256QAM, 1024QAM, 4096QAM
Viterbi rate	2/3, 3/4, 4/5, 5/6, 8/9, 9/10
Guard interval	auto
Spectrum inversion	auto

DVB-S

Bit Error Rate (BER)	CBER (before Viterbi): $1E-7 - 1E-3$ VBER (before Reed Solomon): $1E-7 - 1E-3$
Frequency range	950-2150MHz
Power level	35-100 dBμV, +/-3dB
Modulation Error Rate(MER)	0 - 20dB, +/-0.5dB
Symbole rate	1 Msym/s to 45 Msym/s
Constellation	QPSK
Viterbi rate	1/2, 2/3, 3/4, 5/6, 6/7, 7/8
Spectrum inversion	auto

DVB-S2

Bit Error Rate (BER)	CBER (before LDPC): $1E-7 - 1E-3$ LBER (before BCH): $1E-9 - 1E-5$
Frequency range	950-2150MHz
Power level	35-100 dBμV, +/-3dB
Modulation Error Rate(MER)	0 - 20dB, +/-0.5dB
Symbole rate	1M sym/s to 45 Msym/s
Constellation	QPSK, 8PSK, 16APSK, 32APSK
Viterbi rate	2/5, 1/2, 3/5, 2/3, 3/4, 5/6, 8/9, 9/10
Spectrum inversion	auto

ATV

Frequency range	42-1005MHz
Video Audio System	NTSC_M PAL_G PAL_M PAL_N PAL_K PAL_L PAL_I SECAM_L ECAM_B SECAM_D